

# NCP706A

## 1 A, 1% Precision Very Low Dropout Voltage Regulator with Enable and Active Discharge

The NCP706A is a Very Low Dropout Regulator which provides up to 1 A of load current and maintains excellent output voltage accuracy of 1% including line, load and temperature variations. The operating input voltage range from 2.4 V up to 5.5 V makes this device suitable for Li-ion battery powered products as well as post-regulation applications. The product is available in 3.0 V fixed output voltage option. NCP706A is fully protected against overheating and output short circuit.

Very small 8-pin XDFN8 1.6 x 1.2, 04P package makes the device especially suitable for space constrained portable applications such as tablets and smartphones. Parts feature active output discharge function.

### Features

- Operating Input Voltage Range: 2.4 V to 5.5 V
- Fixed Output Voltage Option: 3.0 V  
Other Output Voltage Options Available on Request.
- Low Quiescent Current of Typ. 200  $\mu$ A
- Very Low Dropout: 155 mV Max. at  $I_{OUT} = 1$  A
- $\pm 1\%$  Accuracy Over Load/Line/Temperature
- High PSRR: 60 dB at 1 kHz
- Internal Soft-Start to Limit the Inrush Current
- Thermal Shutdown and Current Limit Protections
- Stable with a 1.0  $\mu$ F Ceramic Output Capacitor
- Available in XDFN8 1.6 x 1.2, 04P 8-pin Package
- Active Output Discharge
- These are Pb-Free Devices

### Typical Applications

- Tablets, Smartphones,
- Wireless Handsets, Portable Media Players
- Portable Medical Equipment
- Other Battery Powered Applications




Figure 1. Typical Application Schematic




ON Semiconductor®

[www.onsemi.com](http://www.onsemi.com)



XDFN8  
CASE 711AS


### MARKING DIAGRAM




AE = Specific Device Code  
M = Date Code  
▪ = Pb-Free Package

(Note: Microdot may be in either location)

### PIN CONNECTION



(Top View)



(Bottom View)

### ORDERING INFORMATION

See detailed ordering, marking and shipping information on page 8 of this data sheet.

# NCP706A




Figure 2. Simplified Internal Schematic Block Diagram

## PIN FUNCTION DESCRIPTION

| Pin No.<br>XDFN8 | Pin Name    | Description                                                                                                                                                                              |
|------------------|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1                | OUT         | Regulated output voltage. A minimum 1.0 $\mu$ F ceramic capacitor is needed from this pin to ground to assure stability.                                                                 |
| 2                | OUT         |                                                                                                                                                                                          |
| 3                | N/C         | Not connected. This pin can be tied to ground to improve thermal dissipation.                                                                                                            |
| 4                | SNS         | Remote sense connection. This pin should be connected to the output voltage rail.                                                                                                        |
| 5                | GND         | Power supply ground.                                                                                                                                                                     |
| 6                | EN          | Enable pin. Driving EN over 0.9 V turns on the regulator. Driving EN below 0.4 V puts the regulator into shutdown mode.                                                                  |
| 7                | IN          | Input pin. A small capacitor is needed from this pin to ground to assure stability.                                                                                                      |
| 8                | IN          |                                                                                                                                                                                          |
| –                | Exposed Pad | This pad enhances thermal performance and is electrically connected to GND. It is recommended that the exposed pad is connected to the ground plane on the board or otherwise left open. |

# NCP706A

## ABSOLUTE MAXIMUM RATINGS

| Rating                                    | Symbol       | Value                      | Unit |
|-------------------------------------------|--------------|----------------------------|------|
| Input Voltage (Note 1)                    | $V_{IN}$     | -0.3 V to 6 V              | V    |
| Output Voltage                            | $V_{OUT}$    | -0.3 V to $V_{IN} + 0.3$ V | V    |
| Enable Input                              | $V_{EN}$     | -0.3 V to $V_{IN} + 0.3$ V | V    |
| Output Short Circuit Duration             | $t_{SC}$     | Indefinite                 | s    |
| Maximum Junction Temperature              | $T_{J(MAX)}$ | 150                        | °C   |
| Storage Temperature                       | $T_{STG}$    | -55 to 150                 | °C   |
| ESD Capability, Human Body Model (Note 2) | $ESD_{HBM}$  | 2000                       | V    |
| ESD Capability, Machine Model (Note 2)    | $ESD_{MM}$   | 200                        | V    |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.
2. This device series incorporates ESD protection and is tested by the following methods:  
 ESD Human Body Model tested per EIA/JESD22-A114  
 ESD Machine Model tested per EIA/JESD22-A115  
 Latch-up Current Maximum Rating tested per JEDEC standard: JESD78

## THERMAL CHARACTERISTICS

| Rating                                                                             | Symbol          | Value | Unit |
|------------------------------------------------------------------------------------|-----------------|-------|------|
| Thermal Characteristics, XDFN8 1.6x1.2, 04P<br>Thermal Resistance, Junction-to-Air | $R_{\theta JA}$ | 160   | °C/W |

# NCP706A

## ELECTRICAL CHARACTERISTICS – VOLTAGE VERSION 3.0 V

–40°C ≤ T<sub>J</sub> ≤ 125°C; V<sub>IN</sub> = V<sub>OUT(NOM)</sub> + 0.3 V or 3.3 V, whichever is greater; I<sub>OUT</sub> = 10 mA, C<sub>IN</sub> = C<sub>OUT</sub> = 1.0 μF, V<sub>EN</sub> = 0.9 V, unless otherwise noted. Typical values are at T<sub>J</sub> = +25°C. (Note 3)

| Parameter                                     | Test Conditions                                                                                                                | Symbol                                   | Min  | Typ  | Max            | Unit              |
|-----------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|------------------------------------------|------|------|----------------|-------------------|
| Operating Input Voltage                       |                                                                                                                                | V <sub>IN</sub>                          | 2.4  |      | 5.5            | V                 |
| Undervoltage lock-out                         | V <sub>IN</sub> rising, I <sub>OUT</sub> = 0                                                                                   | UVLO                                     | 1.2  | 1.6  | 1.9            | V                 |
| Output Voltage Accuracy                       | V <sub>OUT</sub> + 0.3 V ≤ V <sub>IN</sub> ≤ 4.5 V, I <sub>OUT</sub> = 0 – 1 A                                                 | V <sub>OUT</sub>                         | 2.97 | 3.0  | 3.03           | V                 |
| Line Regulation                               | V <sub>OUT</sub> + 0.3 V ≤ V <sub>IN</sub> ≤ 4.5 V, I <sub>OUT</sub> = 10 mA                                                   | Reg <sub>LINE</sub>                      |      | 2    |                | mV                |
| Load Regulation                               | I <sub>OUT</sub> = 0 mA to 1 A, V <sub>IN</sub> = 3.3 V                                                                        | Reg <sub>LOAD</sub>                      |      | 2    |                | mV                |
| Load Transient                                | I <sub>OUT</sub> = 10 mA to 1 A in 10 μs, V <sub>IN</sub> = 3.5 V<br>C <sub>OUT</sub> = 10 μF                                  | Tran <sub>LOAD</sub>                     |      | ±120 |                | mV                |
| Dropout voltage (Note 4)                      | I <sub>OUT</sub> = 1 A, V <sub>OUT(nom)</sub> = 3.0 V                                                                          | V <sub>DO</sub>                          |      | 155  | 230            | mV                |
| Output Current Limit                          | V <sub>OUT</sub> = 90% V <sub>OUT(nom)</sub>                                                                                   | I <sub>CL</sub>                          | 1.1  |      |                | A                 |
| Quiescent current                             | I <sub>OUT</sub> = 0 mA                                                                                                        | I <sub>Q</sub>                           |      | 170  | 230            | μA                |
| Ground current                                | I <sub>OUT</sub> = 1 A                                                                                                         | I <sub>GND</sub>                         |      | 200  |                | μA                |
| Shutdown current                              | V <sub>EN</sub> ≤ 0 V, V <sub>IN</sub> = 2.0 to 5.5 V                                                                          |                                          |      | 0.1  | 1              | μA                |
| EN Pin High Threshold<br>EN Pin Low Threshold | V <sub>EN</sub> Voltage increasing<br>V <sub>EN</sub> Voltage decreasing                                                       | V <sub>EN_HI</sub><br>V <sub>EN_LO</sub> | 0.9  |      | 0.4            | V                 |
| EN Pin Input Current                          | V <sub>EN</sub> = 5.5 V                                                                                                        | I <sub>EN</sub>                          |      | 100  | 500            | nA                |
| Turn-on Time                                  | C <sub>OUT</sub> = 4.7 μF, from assertion EN pin to 98%<br>V <sub>out(nom)</sub>                                               | t <sub>ON</sub>                          |      | 150  |                | μs                |
| Power Supply Rejection Ratio                  | V <sub>IN</sub> = 3.5 V + 200 mVpp modulation, V <sub>OUT</sub> = 3.0 V<br>I <sub>OUT</sub> = 0.5 A, C <sub>OUT</sub> = 4.7 μF | f = 100 Hz<br>f = 1 kHz<br>f = 10 kHz    | PSRR |      | 65<br>58<br>52 | dB                |
| Output Noise Voltage                          | V <sub>OUT</sub> = 3.0 V, V <sub>IN</sub> = 4.0 V, I <sub>OUT</sub> = 0.5 A<br>f = 100 Hz to 100 kHz                           | V <sub>NOISE</sub>                       |      | 300  |                | μV <sub>rms</sub> |
| Thermal Shutdown Temperature                  | Temperature increasing from T <sub>J</sub> = +25°C                                                                             | T <sub>SD</sub>                          |      | 160  |                | °C                |
| Thermal Shutdown Hysteresis                   | Temperature falling from T <sub>SD</sub>                                                                                       | T <sub>SDH</sub>                         |      | 20   |                | °C                |
| Active Output Discharge                       | V <sub>EN</sub> ≤ 0.4 V, V <sub>IN</sub> = 4.5 V                                                                               | R <sub>DIS</sub>                         |      | 60   |                | Ω                 |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

- Performance guaranteed over the indicated operating temperature range by design and/or characterization production tested at T<sub>J</sub> = T<sub>A</sub> = 25°C. Low duty cycle pulse techniques are used during testing to maintain the junction temperature as close to ambient as possible.
- Characterized when V<sub>OUT</sub> falls 90 mV below the regulated voltage at V<sub>IN</sub> = 3.3 V, I<sub>OUT</sub> = 10 mA.

## TYPICAL CHARACTERISTICS




Figure 3. Output Voltage vs. Temperature




Figure 4. Output Voltage vs. Input Voltage




Figure 5. Quiescent Current vs. Input Voltage




Figure 6. Ground Current vs. Output Current




Figure 7. Short Current Limitation vs. Input Voltage




Figure 8. Dropout Voltage vs. Output Current

TYPICAL CHARACTERISTICS




Figure 9. Reverse Leakage Current in Shutdown




Figure 10. PSRR vs. Frequency & Output Capacitor




Figure 11. PSRR vs. Frequency & Output Current




Figure 12. Output Noise Density vs. Frequency

TYPICAL CHARACTERISTICS




Figure 13. Turn-on by Coupled Input and Enable Pins




Figure 14. Turn-on by Enable Signal




Figure 15. Line Transient Response




Figure 16. Load Transient Response




Figure 17. Turn-off by Enable Signal

## APPLICATIONS INFORMATION

**Input Decoupling (Cin)**

A 1.0  $\mu\text{F}$  capacitor either ceramic or tantalum is recommended and should be connected as close as possible to the pins of NCP706A device. Higher values and lower ESR will improve the overall line transient response.

**Output Decoupling (Cout)**

The minimum decoupling value for NCP706AMX300TAG device is 1  $\mu\text{F}$ . The regulator accepts ceramic chip capacitors MLCC. If a tantalum capacitor is used, and its ESR is large, the loop oscillation may result. Larger values improve noise rejection and PSRR.

**Enable Operation**

The enable pin EN will turn on or off the regulator. These limits of threshold are covered in the electrical specification section of this data sheet. If the enable is not used then the pin should be connected to  $V_{\text{IN}}$ .

**Hints**

Please be sure the  $V_{\text{IN}}$  and GND lines are sufficiently wide. If their impedance is high, noise pickup or unstable operation may result.

Set external components, especially the output capacitor, as close as possible to the circuit.

The sense pin SNS trace is recommended to be kept as far from noisy power traces as possible and as close to load as possible.

**Thermal**

As power across the NCP706A increases, it might become necessary to provide some thermal relief. The maximum power dissipation supported by the device is dependent upon board design and layout. Mounting pad configuration on the PCB, the board material, and also the ambient temperature affect the rate of temperature rise for the part. This is stating that when the NCP706A has good thermal conductivity through the PCB, the junction temperature will be relatively low with high power dissipation.

The power dissipation across the device can be roughly represented by the equation:

$$P_D = (V_{\text{IN}} - V_{\text{OUT}}) * I_{\text{OUT}} \text{ [W]} \quad (\text{eq. 1})$$

The maximum power dissipation depends on the thermal resistance of the case and circuit board, the temperature differential between the junction and ambient, PCB orientation and the rate of air flow.

The maximum allowable power dissipation can be calculated using the following equation:

$$P_{\text{MAX}} = (T_J - T_A) / \theta_{JA} \text{ [W]} \quad (\text{eq. 2})$$

Where  $(T_J - T_A)$  is the temperature differential between the junction and the surrounding environment and  $\theta_{JA}$  is the thermal resistance from the junction to the ambient.

Connecting the exposed pad and non connected pin 3 to a large ground pad or plane helps to conduct away heat and improves thermal relief.

**ORDERING INFORMATION**

| Device          | Nominal Ooutput Voltage | Marking | Package            | Shipping <sup>†</sup> |
|-----------------|-------------------------|---------|--------------------|-----------------------|
| NCP706AMX300TAG | 3.0 V                   | AE      | XDFN8<br>(Pb-Free) | 3000 / Tape & Reel    |

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

# MECHANICAL CASE OUTLINE

## PACKAGE DIMENSIONS



ON Semiconductor®



SCALE 4:1

**XDFN8 1.6x1.2, 0.4P**  
CASE 711AS  
ISSUE D

DATE 08 DEC 2015




### NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. COPLANARITY APPLIES TO THE EXPOSED PAD AS WELL AS THE TERMINALS.

| DIM | MILLIMETERS |       |       |
|-----|-------------|-------|-------|
|     | MIN         | NOM   | MAX   |
| A   | 0.300       | 0.375 | 0.450 |
| A1  | 0.000       | 0.025 | 0.050 |
| b   | 0.130       | 0.180 | 0.230 |
| D   | 1.500       | 1.600 | 1.700 |
| D2  | 1.200       | 1.300 | 1.400 |
| E   | 1.100       | 1.200 | 1.300 |
| E2  | 0.200       | 0.300 | 0.400 |
| e   | 0.40 BSC    |       |       |
| L   | 0.150       | 0.200 | 0.250 |
| L1  | 0.000       | 0.050 | 0.100 |

### GENERIC MARKING DIAGRAM\*




- XX = Specific Device Code  
M = Date Code  
▪ = Pb-Free Package

(Note: Microdot may be in either location)

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "▪", may or may not be present.

### RECOMMENDED MOUNTING FOOTPRINT\*



DIMENSIONS: MILLIMETERS

\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

|                         |                             |                                                                                                                                                                                  |
|-------------------------|-----------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>DOCUMENT NUMBER:</b> | <b>98AON87768E</b>          | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |
| <b>DESCRIPTION:</b>     | <b>XDFN8, 1.6X1.2, 0.4P</b> | <b>PAGE 1 OF 1</b>                                                                                                                                                               |

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

**onsemi**, **Onsemi**, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

### TECHNICAL PUBLICATIONS:

Technical Library: [www.onsemi.com/design/resources/technical-documentation](http://www.onsemi.com/design/resources/technical-documentation)  
onsemi Website: [www.onsemi.com](http://www.onsemi.com)

### ONLINE SUPPORT: [www.onsemi.com/support](http://www.onsemi.com/support)

For additional information, please contact your local Sales Representative at  
[www.onsemi.com/support/sales](http://www.onsemi.com/support/sales)