



Construction Wire



Outline:

- Excellent DC bias capability to handle instantaneous peak current.
- Flat wire winding, achieving very low DC resistance.
- The inductance value and DC bias characteristic are little affected by temperature.
- Magnetically shielded structure, excellent resistance to electromagnetic interference.
- Compact design saves PCB mounting area.





Features:

- Core material: Composite.
- Environmental: RoHS compliant, halogen free.
- Weight: 74.8g
- Moisture Sensitivity: Level (MSL) 1
(Unlimited floor life at <30°C / 85% relative humidity)
- Operating temperature range: -55°C~+155°C
(Including coil's temperature rise).
- Storage temperature range: -55°C~+155°C

Application:

- PV inverter/Industrial control/New energy
- DC /DC converters/Motherboards/Filter
- High current switching regulators

1 Product Dimensions (mm)




Inductance	3.30μH	4.50μH	7.20μH	10.0μH	13.0μH	15.0μH	18.0μH	22.0μH
A(mm)	2.50	2.00	1.60	1.30	1.20	1.10	1.00	0.90
B(mm)	16.2	15.5	16.2	15.8	15.8	16.2	16.2	15.8
C(mm)	3.50	3.00	2.60	2.30	2.20	2.10	2.00	1.90

※ Date code will be changed by manufacture date.

2 Electrical Characteristics

Part No.	Inductance (μH)※1 ±20%	D.C.R. (mΩ)		Isat (A)※2 Typical	Irms (A)※3 Typical
		Typical	Max.		
CPEX2626S-3R3MC	3.30	0.53	0.64	120	60.0
CPEX2626S-4R5MC	4.50	0.75	0.90	100	56.0
CPEX2626S-7R2MC	7.20	1.23	1.48	90.0	44.0
CPEX2626S-100MC	10.0	1.84	2.20	64.0	36.0
CPEX2626S-130MC	13.0	2.18	2.62	59.0	33.0
CPEX2626S-150MC	15.0	2.49	2.99	53.0	30.0
CPEX2626S-180MC	18.0	2.97	3.56	48.0	28.0
CPEX2626S-220MC	22.0	3.88	4.66	43.0	25.0



All data is tested on 25°C ambient temperature

1. Inductance measure condition at 100kHz, 0.1V.
2. Isat: the actual value of DC current when the Inductance decrease 30% of its initial Value.
3. Irms: The actual value of DC current when the Temperature rise is ΔT50°C (Ta=25°C)

3 How to Order

CPEX2626S-4R5MC









Model

Dimensions









Value Code

Coating

4 Saturation Current vs Temperature Rise Current Curve




5 L vs Frequency




6 Impedance vs Frequency


CPEX2626S-3R3MC




CPEX2626S-4R5MC




CPEX2626S-7R2MC




CPEX2626S-100MC




CPEX2626S-130MC




CPEX2626S-150MC



CPEX2626S-180MC




CPEX2626S-220MC



7 Packing Specification


7.1 Plastic Tray Dimensions (mm)



Packaging Unit (Pcs)	Material
16	APET

L typ	W typ	H typ	No. of Tray (Pcs)	Packaging Unit(Pcs)	Material
265	205	32	1	16	Paper

7.2 Packing(mm)



L typ	W typ	H typ	No. of Inner Carton	Packaging Unit(Pcs)	Material
275	232	261	6	96	Paper

8 Notice of Use

- 8.1 Special remind:Circuit design, component placement, PCB size and thickness, cooling system and etc. all will affect the product temperature. Please verify the product temperature in the final application.
- 8.2 Product in packing storage condition:temperature 5~40°C, RH≤70%.
If taking out for use, the remaining products should be sealed in plastic bags and preserved in accordance with the above conditions, to avoid oxidation of terminals (electrodes), affecting soldering status.
- 8.3 A storage of Codaca Electronic products for longer than 12 months is not recommended, Within other effects, the terminals may suffer degradation, resulting in bad solderability. Therefore, all products shall be used within the period of 12 months based on the day of shipment.
- 8.4 Do not keep products in unsuitable storage conditions, such as areas susceptible to high temperatures, high humidity, dust or corrosion.
- 8.5 Always handle products with care.
- 8.6 Don't touch electrodes directly with bare hands as oil secretions may inhibit soldering.
Always ensure optimum conditions for soldering.
- 8.7 When this product will be used on a similar or new project to the original one,
sometimes it might be unable to satisfy the specifications due to different condition of usage.
- 8.8 This inductor itself does not have any protective function in abnormal condition, such as overload, short-circuit, open-circuit conditions, etc. Therefore, it shall be confirmed that there is no risk of smoke, fire, dielectric withstand voltage, insulation resistance, etc., or use in abnormal conditions protective devices or protection circuit in the end product.
- 8.9 Hi-Pot test with higher voltage than spec value will damage insulating material and shorten its life.
- 8.10 If using in potting compound, the magnet wire coating might be damaged, please consult with us.
- 8.11 Refrain from rinsing coils. If necessary, please consult with us.
- * 8.12 Codaca Electronic products without "V" prefix are qualified for industrial product requirement , and with "V" prefix are qualified for AEC-Q200, but it doesn't mean that Codaca Electronic products can absolutely meet specific industry norms and quality test standards in automotive electronics or more strict application fields . Codaca Electronic will be exempted from being responsible for the consequences of using Codaca products in automotive electronic or higher application field related to safety when without being aware of it.