Note: This datasheet may be out of date

Please download the latest datasheet of CDSCB10M7GA136-R0 from the official website of Murata

Manufacturing Co., Ltd. https://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GA136-R0

CDSCB10M7GA136-R0










Appearance & Shape










Communication Equipment/Audio Visual Equipment



Packaging Information

Packaging	Specifications	Minimum Order Quantity
R0	180mm Embossed Tape	2000



CDSCB10M7 series forms a resonator on a piezoelectric ceramic substrate. In combination with ICs, this type obtains stable demodulation characteristics in a wide bandwidth. They have 1.0mm max. thickness and small mounting area (4.5x2.0mm).

Features

- 1. Compact and high reliability and recommended for automotive applications.
- 2. Can be combined with various ICs. The IC is determined by the last number in the part number.
- 3. Stable demodulation characteristics can be obtained without adjustment.
- 4. Stable temperature characteristics
- 5. Available lead (Pb) free solder reflow.

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/12/26

Manufacturing Co., Ltd. https://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GA136-R0

CDSCB10M7GA136-R0



Operating Temperature Range	-20°C to 80°C
Shape	SMD
Elements	1
Center Frequency	10.700MHz
Center Frequency Tolerance	±30kHz
Nominal Center Value	No
Recovered Audio 3dB BW	140kHzmin.
Area of Distortion	[at fo]
Recovered Audio Output	120mVmin.
IC	TH7122
IC Maker	MELEXIS
Detection Method	quadrature type

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering




URL: https://www.murata.com/

Last updated :2019/12/26


Manufacturing Co., Ltd. https://www.murata.com/en-us/products/productdetail?partno=CDSCB10M7GA136-R0

CDSCB10M7GA136-R0





Frequency Characteristics



Measurement Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/