

High-Efficiency, 3-Output, Low-Voltage DC-DC Converter

General Description

The MAX20419 is a high-efficiency, 3-output, low-voltage DC-DC converter IC. OUT1 boosts the input supply to 5V at up to 750mA, while two synchronous step-down converters operate from a 3.0V to 5.5V input voltage range and provide a 0.8V to 3.8V output voltage range at up to 3.6A. The boost converter achieves $\pm 1.9\%$ and the buck converters achieve $\pm 1.4\%$ output error over load, line, and temperature range. The IC features a 2.2MHz fixed-frequency pulse-width modulation (PWM) mode for better noise immunity and load-transient response, and a pulse-frequency-modulation mode (skip) for increased efficiency during light-load operation. The 2.2MHz frequency operation allows the use of all-ceramic capacitors and minimizes external components. The programmable spread-spectrum frequency modulation minimizes radiated electromagnetic emissions. Integrated low $R_{DS(ON)}$ switches improve efficiency at heavy loads, and make the layout a much simpler task with respect to discrete solutions.

The IC is offered with factory-preset output voltages (see the *Ordering Information/Selector Guide* for available options). Other features include soft-start, overcurrent, and over-temperature protections. The MAX20419 also has several redundancy and diagnostic features for compatibility with ASIL-rated applications.

Applications

- Advanced Driver-Assistance Systems (ADAS)
- Infotainment
- SoC Power

Benefits and Features

- Multiple Functions for Small Size
 - Synchronous 750mA Boost Converter
 - Fixed at 5V Output
 - Dual Synchronous Buck Converters up to 3.6A
 - Factory Configurable from 0.8V to 3.8V in 25mV Steps
 - Programmable Windowed Watchdog
 - 3.0V to 5.5V Operating Supply Voltage
 - 2.2MHz Operation
 - Individual $\overline{\text{RESET}}$ Outputs
 - High-Precision Performance
 - $\pm 1.9\%$ Output-Voltage Accuracy (OUT1) and $\pm 1.4\%$ Output-Voltage Accuracy (OUT2, OUT3)
 - $\pm 1.3\%$ OV/UV Monitoring (OUT1–OUT3, PV)
 - Excellent Load-Transient Performance
- Diagnostics and Redundant Circuits
 - ASIL C Compliant
 - Redundant Reference
 - Fail Safe on Open Pins
 - Shorted Pin Detection on $\overline{\text{RESET1}}$ – $\overline{\text{RESET3}}$
 - Input Overvoltage Detection
- Robust for the Automotive Environment
 - Current Mode, Forced-PWM, and Skip Operation
 - Overtemperature and Short-Circuit Protection
 - 24-Pin (4mm x 4mm) TQFN with Exposed Pad
 - -40°C to $+125^{\circ}\text{C}$ Automotive Temperature Range

Visit [Web Support](#) to complete the nondisclosure agreement (NDA) required to receive additional product information.

Rev. 14

DOCUMENT FEEDBACK

TECHNICAL SUPPORT

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

