

PS9924

Data Sheet

HIGH CMR, 10 Mbps OPEN COLLECTOR OUTPUT TYPE, 8-PIN
 LSDIP PHOTOCOUPLER FOR CREEPAGE DISTANCE OF 14.5 mm


R08DS0059EJ0100
 Rev.1.00
 Jun 28, 2013

DESCRIPTION

The PS9924 is an optical coupled high-speed, active low type isolator containing a GaAlAs LED on the input side and a photodiode and a signal processing circuit on the output side on one chip.

FEATURES

- Long creepage distance (14.5 mm MIN.)
- High common mode transient immunity (CM_H , $CM_L = \pm 15 \text{ kV}/\mu\text{s}$ MIN.)
- High-speed response ($t_{PHL} = 100 \text{ ns}$ MAX., $t_{PLH} = 100 \text{ ns}$ MAX.)
- Low power consumption ($V_{CC} = 3.3/5\text{V}$)
- 8-pin LSDIP (Long Creepage SDIP) type
- Embossed tape product: PS9924-F3: 1 000 pcs/reel
- Pb-Free and Halogen Free product
- Safety standards
 - UL approved: No. E72422
 - CSA approved: No. CA 101391 (CA5A, CAN/CSA-C22.2 60065, 60950)
 - SEMKO approved (EN 60065, EN 60950)
 - DIN EN 60747-5-5 (VDE 0884-5) approved (Option)




APPLICATIONS



- Industrial inverter
- Solar inverter

The mark <R> shows major revised points.

The revised points can be easily searched by copying an "<R>" in the PDF file and specifying it in the "Find what:" field.

PS9924**PACKAGE DIMENSIONS (UNIT: mm)****PHOTOCOUPLER CONSTRUCTION**

Parameter	MIN.
Air Distance	14.5 mm
Creepage Distance	14.5 mm
Isolation Distance	0.4 mm

PS9924**BLOCK DIAGRAM****MARKING EXAMPLE**

PS9924

ORDERING INFORMATION

Part Number	Order Number	Solder Plating Specification	Packing Style	Safety Standard Approval	Application Part Number ^{*1}
PS9924	PS9924-Y-AX	Pb-Free and Halogen Free (Ni/Pd/Au)	10 pcs (Tape 10 pcs cut)	Standard products (UL, CSA, SEMKO approved)	PS9924
PS9924-F3	PS9924-Y-F3-AX		Embossed Tape 1 000 pcs/reel		
PS9924-V	PS9924-Y-V-AX		10 pcs (Tape 10 pcs cut)	DIN EN 60747-5-5 (VDE 0884-5) approved (Option)	
PS9924-V-F3	PS9924-Y-V-F3-AX		Embossed Tape 1 000 pcs/reel		

Note: ^{*1}. For the application of the Safety Standard, following part number should be used.

ABSOLUTE MAXIMUM RATINGS (T_A = 25°C, unless otherwise specified)

	Parameter	Symbol	Ratings	Unit
Diode	Forward Current	I _F	25	mA
	Reverse Voltage	V _R	5	V
	Power Dissipation ^{*1}	P _D	45	mW
Detector	Supply Voltage	V _{CC}	7	V
	Output Voltage	V _O	7	V
	Output Current	I _O	25	mA
	Power Dissipation ^{*2}	P _C	250	mW
Isolation Voltage ^{*3}		BV	7 500	Vr.m.s.
Operating Ambient Temperature		T _A	−40 to +110	°C
Storage Temperature		T _{stg}	−55 to +125	°C

Notes: ^{*1}. Reduced to 0.8 mW/°C at T_A = 85°C or more.

^{*2}. Reduced to 5.2 mW/°C at T_A = 85°C or more.

^{*3} AC voltage for 1 minute at T_A = 25°C, RH = 60% between input and output.

Pins 1-4 shorted together, 5-8 shorted together.

RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	MIN.	TYP.	MAX.	Unit
Low Level Forward Voltage	V _{F(OFF)}	−2		0.8	V
High Level Forward Current	I _{F(ON)}	8	10	12	mA
Supply Voltage	V _{CC}	2.7		5.5	V
Pull-up Resistor	R _L	330		4k	Ω


<R> **ELECTRICAL CHARACTERISTICS ($T_A = -40$ to $+110^\circ\text{C}$, unless otherwise specified)**

Parameter		Symbol	Conditions	MIN.	TYP. ^{*1}	MAX.	Unit
Diode	Forward Voltage	V_F	$I_F = 10\text{ mA}$, $T_A = 25^\circ\text{C}$	1.3	1.56	1.8	V
	Reverse Current	I_R	$V_R = 3\text{ V}$, $T_A = 25^\circ\text{C}$			10	μA
	Terminal Capacitance	C_t	$f = 1\text{ MHz}$, $V_F = 0\text{ V}$, $T_A = 25^\circ\text{C}$		30		pF
Detector	High Level Output Current	I_{OH}	$V_{CC} = V_O = 3.3\text{ V}$, $V_F = 0.8\text{ V}$		1	80	μA
			$V_{CC} = V_O = 5.5\text{ V}$, $V_F = 0.8\text{ V}$		1	100	
	Low Level Output Voltage	V_{OL}	$V_{CC} = 3.3\text{ V}$, $I_F = 10\text{ mA}$, $I_{OL} = 13\text{ mA}$		0.2	0.6	V
			$V_{CC} = 5.5\text{ V}$, $I_F = 10\text{ mA}$, $I_{OL} = 13\text{ mA}$				
	High Level Supply Current	I_{CCH}	$V_{CC} = 3.3\text{ V}$, $I_F = 0\text{ mA}$, $V_O = \text{open}$		2	7	mA
			$V_{CC} = 5.5\text{ V}$, $I_F = 0\text{ mA}$, $V_O = \text{open}$		3	7	
	Low Level Supply Current	I_{CCL}	$V_{CC} = 3.3\text{ V}$, $I_F = 10\text{ mA}$, $V_O = \text{open}$		4	10	mA
			$V_{CC} = 5.5\text{ V}$, $I_F = 10\text{ mA}$, $V_O = \text{open}$		5	10	
Coupled	Threshold Input Voltage (H $\rightarrow$ L)	I_{FHL}	$V_{CC} = 3.3\text{ V}$, $R_L = 350\ \Omega$, $V_O = 0.8\text{ V}$		2	5	mA
			$V_{CC} = 5.0\text{ V}$, $R_L = 350\ \Omega$, $V_O = 0.8\text{ V}$				
	Isolation Resistance	R_{I-O}	$V_{I-O} = 1\text{ kV}_{DC}$, $RH = 40$ to 60%	10^{11}			Ω
	Isolation Capacitance	C_{I-O}	$V_{I-O} = 0\text{ V}$, $f = 1\text{ MHz}$, $T_A = 25^\circ\text{C}$		1.0		pF
	Propagation Delay Time (H $\rightarrow$ L) ^{*2}	t_{PHL}	$V_{CC} = 3.3\text{ V}$, $I_F = 10\text{ mA}$, $R_L = 350\ \Omega$, $C_L = 15\text{ pF}$	$T_A = 25^\circ\text{C}$	45	75	ns
				$T_A = -40^\circ\text{C}$ to 110°C		100	
			$V_{CC} = 5\text{ V}$, $I_F = 10\text{ mA}$, $R_L = 350\ \Omega$, $C_L = 15\text{ pF}$	$T_A = 25^\circ\text{C}$	45	75	
				$T_A = -40^\circ\text{C}$ to 110°C		100	
	Propagation Delay Time (L $\rightarrow$ H) ^{*2}	t_{PLH}	$V_{CC} = 3.3\text{ V}$, $I_F = 10\text{ mA}$, $R_L = 350\ \Omega$, $C_L = 15\text{ pF}$	$T_A = 25^\circ\text{C}$	40	75	ns
				$T_A = -40^\circ\text{C}$ to 110°C		100	
			$V_{CC} = 5\text{ V}$, $I_F = 10\text{ mA}$, $R_L = 350\ \Omega$, $C_L = 15\text{ pF}$	$T_A = 25^\circ\text{C}$	40	75	
				$T_A = -40^\circ\text{C}$ to 110°C		100	
	Pulse Width Distortion (PWD) ^{*2}	$ t_{PHL} - t_{PLH} $	$V_{CC} = 3.3/5\text{ V}$, $I_F = 10\text{ mA}$, $R_L = 350\ \Omega$, $C_L = 15\text{ pF}$		5	35	ns
	Propagation Delay Skew ^{*2}	t_{psk}				40	
	Rise Time ^{*2}	t_r			20		
	Fall Time ^{*2}	t_f			5		
	Common Mode Transient Immunity at High Level Output ^{*3}	CM_H	$V_{CC} = 3.3/5\text{ V}$, $I_F = 0\text{ mA}$, $V_O > 2\text{ V}$, $R_L = 350\ \Omega$, $V_{CM} = 1\text{ kV}$, $T_A = 25^\circ\text{C}$	15	20		kV/ μs
	Common Mode Transient Immunity at Low Level Output ^{*3}	CM_L	$V_{CC} = 3.3/5\text{ V}$, $I_F = 10\text{ mA}$, $V_O < 0.8\text{ V}$, $R_L = 350\ \Omega$, $V_{CM} = 1\text{ kV}$, $T_A = 25^\circ\text{C}$	15	20		kV/ μs


PS9924

Notes: *1. Typical values at $T_A = 25^\circ\text{C}$


*2. Test circuit for propagation delay time



Remark C_L includes probe and stray wiring capacitance.




*3. Test circuit for common mode transient immunity




Remark C_L includes probe and stray wiring capacitance.

<R> **TYPICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$, unless otherwise specified)**


**MAXIMUM FORWARD CURRENT
vs. AMBIENT TEMPERATURE**




**DETECTOR POWER DISSIPATION
vs. AMBIENT TEMPERATURE**




**FORWARD CURRENT vs.
FORWARD VOLTAGE**




**SUPPLY CURRENT vs.
AMBIENT TEMPERATURE**



**OUTPUT VOLTAGE vs.
FORWARD CURRENT**




**OUTPUT VOLTAGE vs.
FORWARD CURRENT**




Remark The graphs indicate nominal characteristics.


LOW LEVEL OUTPUT VOLTAGE vs.
AMBIENT TEMPERATURE




LOW LEVEL OUTPUT VOLTAGE vs.
AMBIENT TEMPERATURE




THRESHOLD INPUT CURRENT vs.
AMBIENT TEMPERATURE





PROPAGATION DELAY TIME,
PULSE WIDTH DISTORTION
vs. AMBIENT TEMPERATURE




PROPAGATION DELAY TIME,
PULSE WIDTH DISTORTION
vs. AMBIENT TEMPERATURE





Remark The graphs indicate nominal characteristics.

PS9924**PROPAGATION DELAY TIME
vs. FORWARD CURRENT****PROPAGATION DELAY TIME
vs. FORWARD CURRENT**


Remark The graphs indicate nominal characteristics.

TAPING SPECIFICATIONS (UNIT: mm)
Outline and Dimensions (Tape)

Tape Direction

PS9924-F3



Outline and Dimensions (Reel)


Packing: 1 000 pcs/reel

RECOMMENDED MOUNT PAD DIMENSIONS (UNIT: mm)

NOTES ON HANDLING**1. Recommended soldering conditions****(1) Infrared reflow soldering**

- | | |
|---|--|
| • Peak reflow temperature | 260°C or below (package surface temperature) |
| • Time of peak reflow temperature | 10 seconds or less |
| • Time of temperature higher than 220°C | 60 seconds or less |
| • Time to preheat temperature from 120 to 180°C | 120±30 s |
| • Number of reflows | Three |
| • Flux | Rosin flux containing small amount of chlorine (The flux with a maximum chlorine content of 0.2 Wt% is recommended.) |

Recommended Temperature Profile of Infrared Reflow**(2) Wave soldering**

- | | |
|-------------------------|--|
| • Temperature | 260°C or below (molten solder temperature) |
| • Time | 10 seconds or less |
| • Preheating conditions | 120°C or below (package surface temperature) |
| • Number of times | One (Allowed to be dipped in solder including plastic mold portion.) |
| • Flux | Rosin flux containing small amount of chlorine (The flux with a maximum chlorine content of 0.2 Wt% is recommended.) |

(3) Soldering by Soldering Iron

- | | |
|--|--|
| • Peak Temperature (lead part temperature) | 350°C or below |
| • Time (each pins) | 3 seconds or less |
| • Flux | Rosin flux containing small amount of chlorine (The flux with a maximum chlorine content of 0.2 Wt% is recommended.) |

(a) Soldering of leads should be made at the point 1.5 to 2.0 mm from the root of the lead

PS9924**(4) Cautions**

- Fluxes

Avoid removing the residual flux with freon-based and chlorine-based cleaning solvent.

2. Cautions regarding noise

Be aware that when voltage is applied suddenly between the photocoupler's input and output at startup, the output transistor may enter the on state, even if the voltage is within the absolute maximum ratings.

USAGE CAUTIONS

1. This product is weak for static electricity by designed with high-speed integrated circuit so protect against static electricity when handling.
2. By-pass capacitor of more than 0.1 μ F is used between V_{CC} and GND near device. Also, ensure that the distance between the leads of the photocoupler and capacitor is no more than 10 mm.
3. Pin 1, 4 (which is an NC^{*1} pin) can either be connected directly to the GND pin on the LED side or left open. Also, Pin 7 (which is an NC^{*1} pin) can either be connected directly to the GND pin on the detector side or left open. Unconnected pins should not be used as a bypass for signals or for any other similar purpose because this may degrade the internal noise environment of the device.
Note: *1. NC: Non-Connection (No Connection).
4. Avoid storage at a high temperature and high humidity.

Caution	GaAs Products	This product uses gallium arsenide (GaAs). GaAs vapor and powder are hazardous to human health if inhaled or ingested, so please observe the following points. • Follow related laws and ordinances when disposing of the product. If there are no applicable laws and/or ordinances, dispose of the product as recommended below. 1. Commission a disposal company able to (with a license to) collect, transport and dispose of materials that contain arsenic and other such industrial waste materials. 2. Exclude the product from general industrial waste and household garbage, and ensure that the product is controlled (as industrial waste subject to special control) up until final disposal. • Do not burn, destroy, cut, crush, or chemically dissolve the product. • Do not lick the product or in any way allow it to enter the mouth.
----------------	---------------	---

Revision History	PS9924 Data Sheet
-------------------------	--------------------------

Rev.	Date	Description	
		Page	Summary
0.01	Apr 06, 2012	–	First edition issued
1.00	Jun 28, 2013	p.5	Modification of ELECTRICAL CHARACTERISTICS
		pp.7 to 9	Addition of TYPICAL CHARACTERISTICS

All trademarks and registered trademarks are the property of their respective owners.

NOTICE

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. California Eastern Laboratories and Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
2. California Eastern Laboratories has used reasonable care in preparing the information included in this document, but California Eastern Laboratories does not warrant that such information is error free. California Eastern Laboratories and Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
3. California Eastern Laboratories and Renesas Electronics do not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of California Eastern Laboratories or Renesas Electronics or others.
4. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part. California Eastern Laboratories and Renesas Electronics assume no responsibility for any losses incurred by you or third parties arising from such alteration, modification, copy or otherwise misappropriation of Renesas Electronics product.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots etc. "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; and safety equipment etc. Renesas Electronics products are neither intended nor authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems, surgical implantations etc.), or may cause serious property damages (nuclear reactor control systems, military equipment etc.). You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application for which it is not intended. California Eastern Laboratories and Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for which the product is not intended by California Eastern Laboratories or Renesas Electronics.
6. You should use the Renesas Electronics products described in this document within the range specified by California Eastern Laboratories, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. California Eastern Laboratories shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or systems manufactured by you.
8. Please contact a California Eastern Laboratories sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. California Eastern Laboratories and Renesas Electronics assume no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You should not use Renesas Electronics products or technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. When exporting the Renesas Electronics products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations.
10. It is the responsibility of the buyer or distributor of California Eastern Laboratories, who distributes, disposes of, or otherwise places the Renesas Electronics product with a third party, to notify such third party in advance of the contents and conditions set forth in this document, California Eastern Laboratories and Renesas Electronics assume no responsibility for any losses incurred by you or third parties as a result of unauthorized use of Renesas Electronics products.
11. This document may not be reproduced or duplicated in any form, in whole or in part, without prior written consent of California Eastern Laboratories.
12. Please contact a California Eastern Laboratories sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.

NOTE 1: "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.

NOTE 2: "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

NOTE 3: Products and product information are subject to change without notice.

CEL Headquarters • 4590 Patrick Henry Drive, Santa Clara, CA 95054 • Phone (408) 919-2500 • www.cel.com

For a complete list of sales offices, representatives and distributors,
Please visit our website: www.cel.com/contactus